

MODEL	DESCRIPTION	FREQUENCY RANGE	CENTER FREQUENCY	GAIN FREQUENCY	OVERALL LENGTH	WHIP STYLE
<b>UHF Models - Chrome</b>						
B4063	5/8 Wave	406-430 MHz	Tunable	3 dBi	38.1 cm (15.0 in.)	13" Straight
B4065C	Closed Coil Collinear	406-430 MHz	Tunable	5 dBi	100.3 cm (39.5 in.)	37-3/8" Collinear
B4505CS	Closed Coil Collinear w/ Spring	450-470 MHz	Tunable	5 dBi	94.0 cm (37.0 in.)	32-3/4" Collinear
B4505C	Closed Coil Collinear	450-470 MHz	Tunable	5 dBi	89.0 cm (35.0 in.)	32-3/4" Collinear
B4062N	NGP 1/2 Wave	406-430 MHz	Tunable	2.4 dBi	36.3 cm (14.31 in.)	10-5/8" Straight
B4302N	NGP 1/2 Wave	430-450 MHz	Tunable	2.4 dBi	31.8 cm (12.5 in.)	10-5/16" Straight
B4502NS	NGP 1/2 Wave w/Spring	450-470 MHz	Tunable	2.4 dBi	31.8 cm (12.5 in.)	34-1/8" Straight
B4502N	NGP 1/2 Wave	450-470 MHz	Tunable	2.4 dBi	31.8 cm (12.5 in.)	34-1/8" Straight
B4305CN	NGP Closed Coil Collinear	430-450 MHz	Tunable	5 dBi	89.0 cm (35.0 in.)	32-7/8" Collinear
B4505CN	NGP Closed Coil Collinear	450-470 MHz	Tunable	5 dBi	82.6 cm (32.5 in.)	30-1/2" Collinear

MODEL	DESCRIPTION	FREQUENCY RANGE	CENTER FREQUENCY	GAIN FREQUENCY	OVERALL LENGTH	WHIP STYLE
<b>Wideband - VHF Models - Chrome</b>						
CW1503	Base Loaded 5/8 Wave	150-162 MHz	156 MHz	3 dBi	123.1 cm (48.5 in.)	

MODEL	DESCRIPTION	FREQUENCY RANGE	CENTER FREQUENCY	GAIN FREQUENCY	OVERALL LENGTH	WHIP STYLE
<b>Dual-Band VHF &amp; UHF - Chrome</b>						
C144-440C	Closed Coil Collinear	144-156 MHz	144 - 148 MHz 440 - 450 MHz	5 dB 2 dB	95.6 cm (37.625 in.)	35-1/2" Collinear
C144-440CS	Closed Coil Collinear w/ spring	150-162 MHz	150 - 174 MHz 450 - 470 MHz	5 dB 2 dB	85.7 cm (37.3 in.)	33-3/4" Collinear
C150-450C	Closed Coil Collinear	153-169 MHz	144 - 148 MHz 440 - 450 MHz	5 dB 2 dB	80 cm (31.5 in.)	29-3/8" Collinear
C150-450CS	Closed Coil Collinear w/ spring	162-174 MHz	150 - 174 MHz 450 - 470 MHz	5 dB 2 dB	80.3 cm (31.6 in.)	28-1/8" Collinear
<b>Dual-Band VHF &amp; UHF - Black</b>						
CB144-440C	Closed Coil Collinear	144-156 MHz	144 - 148 MHz 440 - 450 MHz	5 dB 2 dB	95.6 cm (37.625 in.)	35-1/2" Collinear